

Due to the current number of different configurations for the i-SPEED 7 range (57,600) we have made an easy to use ‘build a camera wizard’ on the dealer portal (Sales staff only) the wizard will not only generate the correct part number for you but also give you the price for that configuration, this is the preferred method of part number and price generation. However we have also provided the more manual method below for part number generation, it is broken into 9 stages separated by –’s .

Model	Sensor	Buffer * Memory	Camera Case	SSD	Lens	Option	Software	AC Lead
716	C	144	I	500	FD	UFSIRIG	SO	US
713	C	36	I	0	FD	UFS	SO	US
716	M	72	R	500	FG	IRIG	SM	UK
720		96		1TB	CS	200KFPS		EU
726		144		EXT-I	EF			JP
		192		EXT-R				CN
		288						
713 = 713 Camera 716 = 716 Camera 720 = 720 Camera 726 = 726 Camera	C = Color M = Mono	36 = 36GB 72 = 72GB 96 = 96GB 144 = 144GB 192 = 192GB 288 = 288GB	I = Instrumentation R = Rugged	0 = No SSD 500 = 500GB internal SSD 1TB = 1TB internal SSD EXT-I = External xSSD side panel (instrumentation) EXT-R = External xSSD side Panel (rugged)	FD = Nikon F D FG = Nikon F DG CS = C and CS EF = Canon EF	UFS = Ultra fast shutter IRIG = IRIG 200KFPS = 200k frame limit	SO = Control One SM = Control Multi/DAQ	US = United States UK = United Kingdom EU = Europe JP = Japan CN = China

\*Not all memories are available for all models